

PZ2FD14VH

Zener Voltage Regulators

Description

The PZ2FD14VH is packaged in a DFN1006-2L surface mount package that has a power dissipation of 250mW. They are designed to provide voltage regulation protection and are especially attractive in situations where space is at a premium.



Feature

- Standard zener breakdown voltage range 14V
- DFN1006-2L package
- Steady state power rating of 250mW
- ESD rating of class 3(>16kV)per human body model
- RoHS compliant transient


Mechanical Characteristics

- Mounting position: Any
- Qualified max reflow temperature:260°C
- Device meets MSL 1 requirements
- DFN1006-2L without plating

Applications

- Cellular phones
- > Hand held portables
- High density PC boards

Electronics Parameter



Electrical characteristics per line@(unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Reverse Zener Voltage	Vz	I _{ZT} = 5mA	13.35	14	14.75	V
Maximum Zener Impedance	Z _{ZT}	I _{ZT} = 5mA	-	12	30	Ω
Maximum Zener Impedance	Zzĸ	I _{ZK} =1mA	-	20	110	Ω
Reverse Leakage Current	I _R	V _R =10V	-	-	5	μA
Forward Voltage	VF	I _F = 100mA	-	0.9	1.25	V
Max.Capacitance	С	V _R =4V, f = 1MHz	-	-	200	pF


Zener Voltage Regulators

PZ2FD14VH

Absolute maximum rating@25℃

Rating	Symbol	Value	Units
Total Device Dissipation FR-5 Board	PD	250	mW
Thermal Resistance, Junction-to-Ambient	Roja	500	°C/W
Storage Temperature	TJ,TSTG	-65 to +150	Ĉ


Typical Characteristics



Zener Voltage Regulators

PZ2FD14VH

Solder Reflow Recommendation





Peak Temp=257°C, Ramp Rate=0.802deg. °C/sec

Zener Voltage Regulators


PZ2FD14VH

Product dimension (DFN1006-2L)





Dim	Inches		Millimeters		
Dim	MIN	MAX	MIN	МАХ	
А	0.013	0.020	0.34	0.50	
В	0.000	0.002	0.00	0.05	
С	0.037	0.042	0.95	1.075	
D	0.021	0.026	0.55	0.675	
E	0.017	0.021	0.45	0.55	
F	0.007	0.011	0.20	0.30	
н	0.015Typ.		0.40Тур.		
R	0.001	0.005	0.05	0.15	



Ordering information

Device	Package	Shipping	
PZ2FD14VH	DFN1006-2L (Pb-Free)	10000 / Tape & Reel	

IMPORTANT NOTICE

(P) and Prisemi[®] are registered trademarks of Prisemi Electronics Co., Ltd (Prisemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: http://www.prisemi.com For additional information, please contact your local Sales Representative. ©Copyright 2009, Prisemi Electronics Prisemi is a registered trademark of Prisemi Electronics.

All rights are reserved.

www.prisemi.com