## PSBD1DF40V2M



#### **Feature**

- > Metal silicon junction, majority carrier conduction
- For surface mounted applications
- Low power loss, high efficiency

Prisemi®

- High forward surge current capability
- For use in low voltage, high frequency inverters, free wheeling, and polarity protection applications

#### **Mechanical Characteristics**

- Case: SOD-123FL
- > Terminals: Solderable per MIL-STD-750, Method 2026
- > Approx. Weight:15mg/0.00048oz

#### Absolute maximum rating@25°C

Rating	Symbol	Value	Units
Maximum Repetitive Peak Reverse Voltage	V <sub>RRM</sub>	40	V
Maximum RMS voltage	V <sub>RMS</sub>	28	V
Maximum DC Blocking Voltage	V <sub>DC</sub>	40	V
Forward Current @ T <sub>C</sub> = 100°C	I <sub>F(AV)</sub>	2.0	A
Forward Surge Current at t=8.3ms	I <sub>FSM</sub>	50	А
Typical Thermal Resistance <sup>1)</sup>	R <sub>θJA</sub>	70	°C/W
Operating Temperature	TJ	-55 ~ +125	°C
Storage Temperature	T <sub>stg</sub>	-55 ~ +150	°C

Note:


1) P.C.B. mounted with 2.0" X 2.0" (5 X 5 cm) copper pad areas.

### Electrical characteristics per line@25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Leakage Current		V <sub>R</sub> = 5V	-	-	5.0	μA
	I R	V <sub>R</sub> = 40V	-	50	500	
Forward Voltage		I <sub>F</sub> = 1.0A	-	0.39	0.42	v
	V <sub>F</sub>	I <sub>F</sub> = 2.0A	-	0.42	0.45	



SOD-123FL



**Circuit Diagram** 

## Schottky Barrier diode

## PSBD1DF40V2M

## **Typical Characteristics**




Fig.1 Forward Current Derating Curve




Fig.3 Typical Forward Characteristic




Fig.5 Maximum Non-Repetitive Peak Forward Surage Current




Fig.2 Typical Reverse Characteristics






Fig.4 Typical Transient Thermal Impedance


## Schottky Barrier diode

# PSBD1DF40V2M

## Product dimension (SOD-123FL)








Bottom View

∠ALL ROUND

I

Е



Unit:mm

Suggested PCB Layout

Dim	Millimeters		Inches		
	Min	Max	Min	Мах	
A	0.90	1.10	0.035	0.043	
С	0.12	0.20	0.005	0.008	
D	2.60	2.90	0.102	0.114	
E	1.70	1.90	0.067	0.075	
е	0.80	1.10	0.031	0.043	
g	0.70	0.90	0.028	0.035	
H <sub>E</sub>	3.50	3.80	0.138	0.150	
2	7°				


# Ordering information

Device	Package	Reel	Shipping
PSBD1DF40V2M	SOD-123FL (Pb-Free)	7"	3000 / Tape & Reel

## Marking information

# Schottky Barrier diode

## Load with information



# PSBD1DF40V2M

#### IMPORTANT NOTICE

P and Prisemi are registered trademarks of Prisemi Electronics Co., Ltd (Prisemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

> Website: http://www.prisemi.com For additional information, please contact your local Sales Representative. ©Copyright 2009, Prisemi Electronics Prisemi<sup>®</sup>is a registered trademark of Prisemi Electronics. All rights are reserved.