

### PES2AF-PES2JF

# Silicon Rectifiers

#### **Feature**

- > For surface mounted applications
- Low profile package
- Glass Passivated Chip Juntion
- Superfast reverse recovery time
- ➤ Lead free in comply with EU RoHS 2011/65/EU directives




### **Mechanical Characteristics**

- Case: SMAF
- > Terminals: Solderable per MIL-STD-750, Method 2026
- Approx. Weight: 27mg 0.00086oz

### Absolute maximum rating@25℃

Parameter	Symbol	PES2 AF	PES2 BF	PES2 CF	PES2 DF	PES2 EF	PES2 GF	PES2 JF	Units
Maximum Repetitive Peak Reverse Voltage	$V_{RRM}$	50	100	150	200	300	400	600	V
Maximum RMS voltage	$V_{RMS}$	35	70	105	140	210	280	420	V
Maximum DC Blocking Voltage	V <sub>DC</sub>	50	100	150	200	300	400	600	V
Maximum Average Forward Rectified Current at Ta =100 °C	I <sub>F(AV)</sub>				2				А
Peak Forward Surge Current 8.3 ms Single Half Sine Wave Superimposed on Rated Load (JEDEC Method)	IFSM	50					A		
Maximum Forward Voltage at 2 A	$V_{F}$	1 1.25 1.7				1.7	V		
Maximum DC Reverse Current Ta=25 °C at Rated DC Blocking Voltage Ta=125 °C	I <sub>R</sub>	5 100					μΑ		
Typical Junction Capacitance at V <sub>R</sub> =4V, f=1MHz	Cj	60					pF		
Maximum Reverse Recovery Time at $I_F$ =0.5A, $I_R$ =1A, $I_{rr}$ =0.25A	t <sub>rr</sub>	35					nS		
Operating and Storage Temperature Range	$T_j$ , $T_{stg}$	-55 ~ +150					°C		


### **Typical Characteristics**



Note: 1. Rise Time = 7ns, max.

Input Impedance = 1megohm, 22pF.

2. Ries Time = 10ns, max. Source Impedance = 50 ohms.



Set time Base for 10ns/div

Fig.1 Reverse Recovery Time Characteristic And Test Circuit Diagram




Fig.2 Maximum Average Forward Current Rating




Fig.3 Typical Reverse Characteristics




Fig.4 Typical Forward Characteristics






Fig.5 Typical Junction Capacitance


### **Solder Reflow Recommendation**

Peak Temp=257℃, Ramp Rate=0.802deg. ℃/sec




# Product dimension (SMAF)





UNIT		Α	С	D	Ш	е	g	HE	2
mm -	max	1.3	0.23	3.7	2.7	1.6	1.3	4.9	· 7°
	min	1.1	0.18	3.3	2.4	1.3	1.0	4.4	
mil	max	51	9.1	146	106	63	51	193	1
	min	43	7.1	130	94	51	39	173	

# The recommended mounting pad size



# Ordering information

Device	Package	Shipping			
PES2AF-PES2JF	SMAF (Pb-Free)	3000/ Tape & Reel			

#### **IMPORTANT NOTICE**

and Prisemi are registered trademarks of Prisemi Electronics Co., Ltd (Prisemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: http://www.prisemi.com
For additional information, please contact your local Sales Representative.

©Copyright 2009, Prisemi Electronics

Prisemi is a registered trademark of Prisemi Electronics.

All rights are reserved.