

PRS2ABF~PRS2MBF

Surface Mount Fast Recovery Rectifiers

Feature

- For surface mounted applications
- Low profile package
- Glass Passivated Chip Junction
- Easy to pick and place
- Fast reverse recovery time
- Lead free in comply with EU RoHS 2011/65/EU directives

Feature

- Case: SMBF
- > Terminals: Solderable per MIL-STD-750, Method 2026.
- Approx. Weight: 57mg / 0.002oz

Maximum Ratings and Electrical characteristics

Ratings at 25 °C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Parameter	Sym bol	PRS2 ABF	PRS2 BBF	PRS2 DBF	PRS2 GBF	PRS2 JBF	PRS2 KBF	PRS2 MBF	Unit s
Maximum Repetitive Peak Reverse Voltage	V _{RRM}	50	100	200	400	600	800	1000	v
Maximum RMS voltage	V_{RMS}	35	70	140	280	420	560	700	V
Maximum DC Blocking Voltage	V _{DC}	50	100	200	400	600	800	1000	V
Maximum Average Forward Rectified Current at Ta = 65°C	I _{F(AV)}	2					А		
Peak Forward Surge Current 8.3ms Single Half Sine Wave Superimposed on Rated Load(JEDEC Method)	I _{FSM}				50				А
Maximum Instantaneous Forward Voltage at 2A	VF				1.3				V
Maximum DC Reverse Current Ta=25°C at Rated DC Blocking Voltage Ta=125°C	I _R				5 100				μΑ
Typical Junction Capacitance ¹⁾	Cj				40				PF
Maximum Reverse Recovery Time ²⁾	t _{rr}	150 250 500			ns				
Typical Thermal Resistance 3)	$R_{ extsf{ heta}JA}$	65				°C/W			
Operating and Storage Temperature Range	T _J ,T _S tg	-55 to +150				°C			

Note:

- 1. Measured at 1MHz and applied reverse voltage of 4V D.C
- 2. Measured with $I_F = 0.5 A$, $I_R = 1 A$, $I_{rr} = 0.25 A$
- 3. P.C.B. mounted with 0.5 X 0.5" (12.7 X 12.7 mm) copper pad areas.

Surface Mount Fast Recovery Rectifiers

PRS2ABF~PRS2MBF




Fig.1 Forward Current Derating Curve





Fig.2 Typical Reverse Characteristics








Fig.5 Maximum Non-Repetitive Peak Forward Surage Current






Fig.4 Typical Junction Capacitance


Surface Mount Fast Recovery Rectifiers

PRS2ABF~PRS2MBF

Product dimension (SMBF)








Top View



UNIT		А	C	D	E	Η _ε	е	g	2
mm	max	1.3	0.26	4.4	3.7	5.5	2.2	1.0	9°
mm	min	1.1	0.18	4.2	3.5	5.1	1.9	1.0	
mil	max	51	10	173	146	216	86	40	9
	min	43	7	165	138	200	75	40	

The recommended mounting pad size



Ordering information

Device	Package	Shipping		
PRS2ABF~PRS2MBF	SMBF (Pb-Free)	5000/ Tape & Reel		

IMPORTANT NOTICE

Q and **Prisemi** are registered trademarks of **Prisemi Electronics Co., Ltd (P**risemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: http://www.prisemi.com For additional information, please contact your local Sales Representative. ©Copyright 2009, Prisemi Electronics Prisemi[®] is a registered trademark of Prisemi Electronics. All rights are reserved.