

PS3AF-PS3MF

Silicon Rectifiers

Feature

- For surface mounted applications
- Low profile package
- Glass Passivated Chip Juntion
- Superfast reverse recovery time
- Lead free in comply with EU RoHS 2011/65/EU directives

Mechanical Characteristics

- Case: SMAF
- > Terminals: Solderable per MIL-STD-750, Method 2026
- > Approx. Weight: 27mg 0.00086oz

Absolute maximum rating@25°C

Parameter	Symbol	PS3A F	PS3B F	PS3D F	PS3G F	PS3J F	PS3K F	PS3M F	Units
Maximum Repetitive Peak Reverse Voltage	V _{RRM}	50	100	200	400	600	800	1000	V
Maximum RMS voltage	V _{RMS}	35	70	140	280	420	560	700	V
Maximum DC Blocking Voltage	V _{DC}	50	100	200	400	600	800	1000	V
Maximum Average Forward Rectified Current at Ta =65 °C	I _{F(AV)}				3				А
Peak Forward Surge Current 8.3 ms Single Half Sine Wave Superimposed on Rated Load (JEDEC Method)	I _{FSM}	100						A	
Maximum Forward Voltage at 3 A	VF				1.2				V
Maximum DC Reverse Current Ta=25 °C at Rated DC Blocking Voltage Ta=125 °C	I _R				5 250				μA
Typical Junction Capacitance at V _R =4V, f=1MHz	Cj	53				pF			
Typical Thermal Resistance(Note 1)	R _{eja}	13 47					°C/W		
Operating and Storage Temperature Range	Tj, T _{stg}			_	55 ~ +150	0			°C

Note1:Thermal resistance from junction to ambient at 0.375"(9.5mm) lead length, P.C.B. mounted



Silicon Rectifiers

PS3AF-PS3MF

Typical Characteristics



Fig.1 Forward Current Derating Curve





Fig.2 Typical Instaneous Reverse Characteristics



Fig.4 Typical Junction Capacitance

Silicon Rectifiers

PS3AF-PS3MF

Solder Reflow Recommendation



Peak Temp=257°C, Ramp Rate=0.802deg. °C/sec

Silicon Rectifiers

PS3AF-PS3MF

Product dimension (SMAF)









Bottom View

UNIT		А	С	D	Е	е	g	H _E	Z
	max	1.3	0.23	3.7	2.7	1.6	1.3	4.9	
	min	1.1	0.18	3.3	2.4	1.3	1.0	4.4	70
mil	max	51	9.1	146	106	63	51	193	
	min	43	7.1	130	94	51	39	173	

The recommended mounting pad size



Ordering information

Device	Package	Shipping			
PS3AF-PS3MF	SMAF (Pb-Free)	3000/ Tape & Reel			

IMPORTANT NOTICE

(Prisemi[®] are registered trademarks of Prisemi Electronics Co., Ltd (Prisemi), Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

> Website: http://www.prisemi.com For additional information, please contact your local Sales Representative. ©Copyright 2009, Prisemi Electronics Prisemi[®] is a registered trademark of Prisemi Electronics. All rights are reserved.